



## Setting up your UNV Camera

This wired camera offers high quality live HD video images 24/7 making it ideal for use in all sorts of garden and wildlife observation.

Please follow these instructions to get your camera live BEFORE attempting installation.

### Camera to POE & Router quick set up.

*Do not fit the weatherproof RJ45 connectors together until you have tested your camera and are ready to permanently install the kit outside.*

1. Observing the clip position and connect the non-booted end of your long cable into the camera port.
2. Connect the other end of the long cable into the POE injector port marked 'POE'
3. Connect the short cable into the POE injector port marked 'LAN'
4. Connect the other end of the short cable into a spare RJ45 port on your router
5. Plug the mains lead into your POE injector and the other end into a mains power socket and switch on.

*The 12vDC input at the camera is only used where a POE injector is not in use and the project requires direct 12vDC power to this port.*

### Setting up the app.

1. On your smart device download an App called **EZLive-UNV**
  - **Login / Sign up**
  - **Select Region:** United Kingdom
  - **Enter an email address** you wish to use
  - **Enter the verification code** you will have received
  - **Press Next** and enter a password you wish to use
  - ✓ Your EZCloud account has been created, you are logged in
2. Press the **+** icon (*top right*) then select **Add Device**
3. Select '**Scan**' at the bottom of your screen to open your camera.
4. Scan the QR code that comes attached to the manufacturers *Network Bullet Cameras - Quick Guide*
5. Set a **Device Name** and press the **save icon** in the top right of your screen.

Your camera should now be available to view in **My Devices**

**gardenature.co.uk**

801 Fowler Road, Oakwood Business Park North, Clacton on Sea, Essex, CO15 4AA

e-mail: [sales@gardenature.co.uk](mailto:sales@gardenature.co.uk) Telephone: 01255 429931

Vat No: 170 7128 21 Company Reg No: 05604321